

GRAS 45BC-11

KEMAR with Mouth Simulator
and Anthropometric Pinnae for
Low-noise Headset Test, 1-Ch
LEMO



Connection: Traditional Power Supply (200 V/LEMO)

Channel(s): 1

Standards: ANSI: S3.36

Based on IEC 60318-4 and 60318-7

Based on ITU-T Rec. P.57 Type 3.3 and

ITU-T Rec. P.58

Special feature: Built-in power amplifier for mouth simulator

The 45BC-11 KEMAR is configured with anthropometric pinnae and a low-noise ear simulator system for testing of headsets with or without active noise cancellation. Due to its design, realistic measurements in a sound environment as experienced by a human being using a headset is possible. In addition, it is provided with a mouth simulator for testing of the microphone in the headset. Its corresponding two-channel equivalent is [GRAS 45BC-12 KEMAR with Mouth Simulator and Anthropometric Pinnae for Low-noise Headset Test, 2-Ch LEMO.](#)

Introduction

The KEMAR head and torso simulator was introduced by Knowles in 1972 and quickly became the industry standard for hearing-aid manufacturers and research audiologists (visit KEMAR.us to read the full story). It is based on worldwide average human male and female head and torso dimensions. It meets the requirements of ANSI S3.36/ASA58-2012 and IEC 60318-7:2011.

The current KEMAR Head and Torso has the same dimensions and acoustical properties as the original KEMAR, but has been developed further by GRAS to meet the industry's demand for realistic measurements. It provides acoustic diffraction similar to that encountered around the median human head and torso, both in the proximity and in the far field.

As all the preconfigured 45BC KEMARs consist of the same basic 45BC KEMAR Non-configured, plus a set of application specific accessories, the full information about a given KEMAR configuration is obtained by combining the information about the 45BC KEMAR Non-configured and the information for a given configured version as found in the present text. Read about the non-configured KEMAR [here](#).

Design

The 45BC-11 is a KEMAR with mouth simulator, anthropometric pinnae and a low-noise ear simulator for 1-channel low-noise headset test. It is delivered fully configured, individually calibrated and ready for use. In addition to a system calibration certificate, a USB flash memory with simulation data is included.

The accessories specific for this configuration are listed in the Ordering Info tab.

The main configuration specific components of the

45BC-11 are the GRAS 44AA Mouth Simulator, the GRAS 43BB Low-noise Ear Simulator System and the KB5000/KB5001 anthropometric pinnae.

The 44AA Mouth Simulator according to ITU-T Rec. P51 with built-in power amplifier

The maximum continuous signal the mouth can produce in 1/3-octave bands is 100dB re. 20 μ Pa in the frequency range 100Hz to 16kHz. Its loudspeaker accepts an external signal either directly or via its own built-in power amplifier (when power is applied).

The 43BB Low-noise Ear Simulator System

Basically the 43BB consists of an IEC 60318-4 Ear Simulator and a 40HT Low-noise Microphone System.

The built-in microphone is the 40AH Low-noise Ext. Polarized Pressure Microphone which has a specially reduced noise floor in order to achieve a large dynamic range.

Below 10 kHz, the frequency response is identical to that of a standard IEC 60318-4 ear simulator. Above 10 kHz, the differences in the microphone diaphragm impedance results in substantial differences. The standard ear simulator has a high-Q resonance around 13.5 kHz related to the length of the ear canal and the diaphragm impedance. In the low noise version of the ear simulator the single high-Q resonance is replaced by two resonances. Part of the design of the low noise microphone is a filter unit that controls the mechanical resonance of the low noise microphone. The combination of the filter and the low damping of the diaphragm cancels out the high peak of the resonance in the simulator.

The preamplifier is the 26HG which is similar to the GRAS 26AC ¼" Standard Preamplifier, but with a 40 G input impedance to enable low-level noise

measurements. It has an integrated lightweight cable terminated in a 7-pin LEMO connector that plugs into the 26HT Gain and Filter Unit.

To complete the system, a special power module is part of the delivery, i.e. the 12HF 1-Channel Power Module for Low-noise Systems.

Read more about the [43BB Low-noise Ear Simulator System](#).

The Anthropometric Pinna

Compared to the standardized pinna, the anthropometric pinna embodies a number of improvements to the concha and ear canal, combined with increased collapsability of the helix, and improved mounting. It is made of soft silicone, 35 Shore 00 hardness.

The external shape of the pinna is identical to that of the standardized KEMAR pinna, but concha and ear canal have been modified so that they closely mimic the properties of a real human ear. The ear canal has been extended and is now an integral part of the pinna, which seals directly against the ear simulator. Like the human ear, the ear canal has the 1st and 2nd bend, and the interface with the concha is oval. Fit and insertion consistency are much improved over the cylindrically or conically shaped ear canal extensions that are used with the standard pinna.

The flexibility of the outer ear has been improved, and when mounting supra-aural and circum-aural headphones the pinna now collapses against the head very much like a human ear.

In addition to the traditional push mounting from the outside, the pinna is secured with two screws from the inside of KEMAR's head. These two screws ensure that the pinna is held firmly in place. Therefore, it seals perfectly against the ear simulator and the head, and it is therefore possible to mount and

dismount DUTs repeatedly without compromising the seal.

Read more about the [Anthropometric Pinnae](#).

Typical Applications

45BC-11 is configured to meet the consumer electronics industry's need for R&D testing of headsets, including sets with Active Noise Cancellation.

The anatomical shape of the pinna makes it possible to achieve very good fit and sealing with anatomically shaped in-ear transducers. Controlling the insertion depth is easy, leading to good insertion consistency and highly improved repeatability and accuracy of measurements. The improved fit and seal also means that the low frequency response is improved. It will allow you to reproduce bass notes, as well as effectively measure (active & passive) attenuation.

Because it can measure down to and below the threshold of human hearing, it can measure the influence of the electronics on the audio response of the earphones. Its low noise floor and usability above 10 kHz means that measurement results will have a strong correlation with the subjective feedback from test persons and users.

The low inherent noise of the system also means that THD and Rub & Buzz at very low levels can be investigated. The improved collapsability of the pinna, and the built-in mouth simulator makes it well suited for testing of supra-aural and circumaural headsets.

Performance and warranty

KEMAR is made of components from our standard portfolio and are all manufactured of high-quality material and branded parts that were chosen and processed to ensure life-long stability and

robustness. This, enables us to offer 2 years warranty against defective materials and workmanship.

Exceptions: Microphones included in KEMAR as for these our normal 5 year warranty apply. The warranty period for cables is 6 months.

| | | |
|--|---|-------------------------|
| Connector type | | 7-pin LEMO (FGG.1B.307) |
| Set sensitivity @ 250 Hz (± 2 dB) | mV/Pa | 800 |
| Theoretical dynamic range lower limit with GRAS preamplifier | dB(A) | 10.5 |
| Theoretical dynamic range upper limit with GRAS preamplifier @ +28 V / ± 14 V power supply | dB | 113 |
| Temperature range, operation | $^{\circ}\text{C}$ / $^{\circ}\text{F}$ | -30 to 60 / -22 to 140 |
| Temperature range, storage | $^{\circ}\text{C}$ / $^{\circ}\text{F}$ | -40 to 65 / -40 to 149 |
| Humidity range non condensing | % RH | 0 to 95% |
| ANSI standard | | S3.36 |
| IEC standard | | 60318-7 |
| ITU-T recommendations | | P. 58 |
| Weight | g / oz | 11.45 k / 404 |
| MOUTH SIMULATOR | | . |
| Output impedance | Ω | 8 |
| Maximum power, continuous | W | 10 |
| Maximum power, pulsed 2 sec. | W | 50 |
| Input impedance | k Ω | 20 |
| Gain | dB | 10 |
| Input signal, max. | Vrms | 2 |
| Power supply, external | Vdc | 24 |

GRAS Sound & Vibration reserves the right to change specifications without notice.

Included items

| | |
|------------------------------|--|
| GRAS 45BC | KEMAR Head & Torso with GRAS 44AA Mouth Simulator , Non-configured |
| GRAS KB5000 | Large Right Anthropometric Pinna 35 Shore 00 |
| GRAS KB5001 | Large Left Anthropometric Pinna 35 Shore 00 |
| GRAS GR1874 | Ear Simulator Holder |
| GRAS GR0408 | External Ear Canal |
| GRAS GR0409 | Union Nut |
| GRAS AA0035 | BNC to BNC Cable |
| GRAS 46BD | 1/4" CCP Pressure Standard Microphone Set (for mouth calibration) |
| GRAS 43BB-1 | Low-noise Ear Simulator System, comprising: |
| GRAS RA0001 | Right Angled Adapter for 1/2" Microphone and 1/4" Preamplifier |
| GRAS RA0234 | Low-noise Ear Simulator |
| GRAS 26HG-S1 | 1/4" Preamplifier with 0.4 m Integrated Cable |
| GRAS 26HT | Gain and Filter Unit for 40HT |
| GRAS 12HF | 1-Channel Power Module for Low-noise Systems |
| GRAS AA0059 | LEMO 7-pin - LEMO 7-pin Cable, 1 m |
| GRAS AA0035 | BNC to BNC Cable |

Optional items

For Ear Simulator Calibration

| | |
|-----------------------------|--|
| GRAS 42AP | Intelligent Pistonphone (250 Hz or 251.2 Hz, 114 dB +/- 0.05 dB) |
| GRAS 42AA | Pistonphone (250 Hz, 114 dB +/- 0.08 dB) |
| GRAS RA0090 | 94 dB Pistonphone Coupler |

Pinna Simulators

| | |
|-----------------------------|--|
| GRAS KB5000 | Large Right Anthropometric Pinna 35 Shore 00 |
|-----------------------------|--|

| | |
|-----------------------------|---|
| GRAS KB5001 | Large Left Anthropometric Pinna 35 Shore 00 |
| GRAS KB0060 | KEMAR Small Right Ear 55 Shore 00 |
| GRAS KB0061 | KEMAR Small Left Ear 55 Shore 00 |
| GRAS KB0065 | KEMAR Large Right Ear 55 Shore 00 |
| GRAS KB0066 | KEMAR Large Left Ear 55 Shore 00 |
| GRAS KB1060 | KEMAR Small Right Ear, 35 Shore 00 |
| GRAS KB1061 | KEMAR Small Left Ear 35 Shore 00 |
| GRAS KB1065 | KEMAR Large Right Ear 35 Shore 00 |
| GRAS KB1066 | KEMAR Large Left Ear 35 Shore 00 |
| GRAS KB0090 | KEMAR Large Right Ear (VA-Style/SQ) 55 Shore 00 |
| GRAS KB0091 | KEMAR Large Left Ear (VA-Style/SQ) 55 Shore 00 |
| GRAS KB1090 | KEMAR Large Right Ear (VA-Style) 35 Shore 00 |
| GRAS KB1091 | KEMAR Large Left Ear (VA-Style) 35 Shore 00 |

Ear Mould Simulators

| | |
|-----------------------------|--|
| GRAS KB0110 | Ear Mould Simulator for 2 mm Inner diameter tubing |
| GRAS KB0111 | Ear Mould Simulator for 3 mm Inner diameter tubing |

Ear Canal Extension and Microphone Holder Kits (kits with 2 pcs and O-rings)

| | |
|-----------------------------|--|
| GRAS RA0237 | Straight Ear Canal Extension Kit for KEMAR |
| GRAS RA0238 | VA-tapered Ear Canal Extension Kit for KEMAR |
| GRAS RA0239 | Ear canal Extension Kit w. silicone lining for KEMAR |
| GRAS RA0240 | Holder for long 1/2" microphone Kit for KEMAR |
| GRAS RA0241 | Holder for short 1/2" microphone Kit for KEMAR |
| GRAS RA0243 | Holder for 1/2" microphone Kit for KEMAR |
| GRAS RA0244 | O-ring kit for KEMAR, 2 pcs. |
| GRAS RA0249 | Straight Ear Canal Extension Kit for KEMAR, made of POM, for binaural hearing aid test |

| | |
|-------------|---|
| GRAS RA0250 | Tapered Ear Canal Extension Kit for KEMAR, made of POM, for binaural hearing aid test |
|-------------|---|

KEMAR Retrofit Kit for Binaural Hearing Aid Test

[GRAS RA0251](#)

KEMAR Retrofit Kit for Binaural Hearing Aid Test:
The Kit includes Ear Holder Plates, mounting bolts and the RA0249 and RA0250 Ear Canal Extension Kits. Included items are made of POM, Nylon and Teflon.

Cables

[GRAS AA0046](#)

3 m LEMO 7-pin - LEMO 7-pin Cable for Low-noise measuring system

[GRAS AA0047](#)

10 m LEMO 7-pin - LEMO 7-pin Cable for Low-noise measuring system

[GRAS AA0053-CL](#)

Customized length LEMO 7-pin - LEMO 7-pin Cable for Low-noise measuring system. CLXXXX= Cable length in centimeters to be specified by customer

Flight Case

GRAS KM0094

PELI Case for KEMAR

Simulation Model of KEMAR

GRAS KB3000

Simulation Model of KEMAR with large pinnae

GRAS KB3001

Simulation Model of KEMAR with small pinnae

Stand for KEMAR

GRAS AL0026

Loudspeaker stand for KEMAR, Ø 35 mm

Miscellaneous

GRAS KB0000

KEMAR Handbook

GRAS KB0010

T-Shirt for KEMAR

GRAS Sound & Vibration reserves the right to change accessories without notice.

| We Make Microphones

Tradition

Since the establishment in 1994, GRAS has been 100% dedicated to developing and manufacturing high-quality measurement microphones and related acoustic equipment.

Innovation

We work with everybody with an interest in sound or noise within the fields of aerospace, automotive, audiology, consumer electronics, noise monitoring, building acoustics and telecommunications.

Quality

At GRAS we know that in order for you to trust your measurement results; signal quality, stability and robustness are essentials. We design and build them to perform under real life conditions – and beyond.

